

## ELLIOTT ELECTRIC SUPPLY

We Deliver...Lower Cost, Quality Products, & Personal Service

110 Success Blvd 79029-0000, TX Dumas Phone: 806-934-4805 Fax: 806-717-2052



### **61521 3-Phase/Motor Rotation Tester**

| Catalog Number         | 61521   |
|------------------------|---|
| Manufacturer           | Ideal   |
| Description            | 3-Phase/Motor Rotation Tester, Voltage Rating: 100 - 600 Vac (10 - 400 HZ) Nominal For Phase Presence Indication, Amperage Rating: 18 Milamp Maximum Consumption, 3 PH Phase, Temperature Rating: 5 - 131 Deg F Operating, -4 to 158 Deg F Storage, Display: Neon Lamps and Leds, Dimensions: 6 In Height X 2.8 In Width X 1.4 In Depth, Phase Rotary Field Direction: 1 - 600 Vac (2 - 400 HZ), Determination Of Motor Rotation: 1 - 600 Vac (2 - 400 HZ) Requires Greater Than 1/2 Turn, Over Load                            |
|                        | Protection: 550 V (Between  |
| Weight per unit        | · · · · · · · · · · · · · · · · · · ·   |
| Product Category       | 1.1 (lbs/each) Testers & Accessories  |
| Features               | TOSTOTS & MODESSOTTES   |
| amperage rating        | 18 MILAMP Maximum Consumption   |
| dimensions             | / IN Hoight V 2.0 IN Width V 1.4 IN Donth   |
| مانمه امیر             | Negral among And LEDs   |
| Phase                  | 3 Dh  |
| Voltage Rating         | 100 - 600 VAC (10 - 400 HZ) Nominal For Phase Presence<br>Indication  |
| Descriptions           |   |
| Description            | 3-PHASE/MOTOR ROTATION TESTER   |
| extra long description | IDEAL 61-521 3 PHASE MOTOR ROTATION   |
| Features               | Identifies three-phase sequencesIndicates motor rotationChecks for open phasesFor use up to 600V2-year warranty   |
| Long Description       | 3-Phase/Motor Rotation Tester, Voltage Rating: 100 - 600 VAC (10 - 400 HZ) Nominal For Phase Presence Indication, Amperage Rating: 18 MILAMP Maximum Consumption, 3 Ph Phase, Temperature Rating: 5 - 131 DEG F Operating, -4 To 158 DEG F Storage, Display: Neon Lamps And LEDs, Dimensions: 6 IN Height X 2.8 IN Width X 1.4 IN Depth, Phase Rotary Field Direction: 1 - 600 VAC (2 - 400 HZ), Determination Of Motor Rotation: 1 - 600 VAC (2 - 400 HZ) Requires Greater Than 1/2 Turn, Over Load Protection: 550 V (Between |
| Product Type           | 3 Phase Motor Rotation Tester   |
| Special Features       | Identifies three-phase sequence; Indicates motor rotation;<br>Checks for open phases; For use up to 600 V; Meets IEC-1010<br>(EN61010) safety requirements; 2-year warranty; Includes   |

carrying case



# ELLIOTT ELECTRIC SUPPLY

We Deliver...Lower Cost, Quality Products, & Personal Service

110 Success Blvd 79029-0000, TX Dumas Phone: 806-934-4805 Fax: 806-717-2052

| Brand                     | ldeal          |  |
|---------------------------|----------------|--|
| GTIN                      | 00783250615216 |  |
| Manufacturers Part Number | 61-521         |  |
| UPC                       | 783250615216   |  |

#### **Taxonomies, Classifications, and Categories**

| Category Description | TEST EQUIPMENT, TESTERS AND MULTIMETERS |
|----------------------|---|
| Туре                 | 3-Phase/Motor Rotation Tester           |

#### **Packaging**

| Carton 1             |  |
|----------------------|--|
| Weight Per each 1.05 |  |

#### Uses, Certifications, and Standards

| standard           | Meets IEC-1010 (EN61010) Safety Requirements, CE N12966, CAT |
|--------------------|--|
|                    | III 600V   |
| Temperature Rating | 5 - 131 DEG F Operating, -4 To 158 DEG F Storage             |