



MILBANK
ENERGY AT WORK

U2049-RL



| | | | |
|-------------------------------|---|---------------------------|-------------------|
| Catalog Number | U2049-RL | Jaw Quantity | 7 Terminal |
| Marketing Product Description | 7 Terminal Ringless Small Hub Open Lever Bypass | Bypass Type | Lever Bypass |
| UPC | 784572233850 | Number of Meter Positions | 1 Position |
| Length (IN) | 4.844 | Equipment Ground | Grounding Stud |
| Width (IN) | 10 | Hub Opening | Small Hub Opening |
| Height (IN) | 18.5 | Line Side Wire Range | 6 AWG - 350 kcmil |
| Brand Name | Milbank | Load Side Wire Range | 6 AWG - 350 kcmil |
| Type | Ringless Meter Socket | Number Of Receptacles | 0 |
| Application | Meter Socket | | |
| Standard | UL Listed;Type 3R | | |
| Voltage Rating | 600 Volts Alternating Current | | |
| Amperage Rating | 200 Continuous Ampere | | |
| Phase | 3 Phase | | |
| Frequency Rating | 60 Hertz | | |
| Size | 4.844L x 10W x 18.5H | | |
| Number Of Cutouts | 0 | | |
| Cutout Size | No Main Breaker | | |
| Cable Entry | Overhead | | |
| Terminal | Lay in | | |
| Insulation | Glass Polyester | | |
| Mounting | Surface Mount | | |
| Enclosure | G90 Galvanized Steel with Powder Coat Finish | | |

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.



MILBANK
ENERGY AT WORK

U2049-RL



| | |
|-------------------------------|---|
| Catalog Number | U2049-RL |
| Marketing Product Description | 7 Terminal Ringless Small Hub Open Lever Bypass |
| UPC | 784572233850 |
| Length (IN) | 4.844 |
| Width (IN) | 10 |
| Height (IN) | 18.5 |
| Brand Name | Milbank |
| Type | Ringless Meter Socket |
| Application | Meter Socket |
| Standard | UL Listed;Type 3R |
| Voltage Rating | 600 Volts Alternating Current |
| Amperage Rating | 200 Continuous Ampere |
| Phase | 3 Phase |
| Frequency Rating | 60 Hertz |
| Size | 4.844L x 10W x 18.5H |
| Number Of Cutouts | 0 |
| Cutout Size | No Main Breaker |
| Cable Entry | Overhead |
| Terminal | Lay in |
| Insulation | Glass Polyester |
| Mounting | Surface Mount |
| Enclosure | G90 Galvanized Steel with Powder Coat Finish |

| | |
|---------------------------|-------------------|
| Jaw Quantity | 7 Terminal |
| Bypass Type | Lever Bypass |
| Number of Meter Positions | 1 Position |
| Equipment Ground | Grounding Stud |
| Hub Opening | Small Hub Opening |
| Line Side Wire Range | 6 AWG - 350 kcmil |
| Load Side Wire Range | 6 AWG - 350 kcmil |
| Number Of Receptacles | 0 |

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.